

Remotes

Remote - ME-RC

The Magnum Remote is designed to be simple to use while offering full menu features for set-up.

Easy-to-read: The large LCD screen and at-a-glance LEDs display the inverter/charger status in a straightforward way. Soft keys give simple access to menus and a rotary encoder knob makes it easy to quickly scroll through menus and select settings.

Non-volatile memory: Critical settings are saved even if the power is disconnected.

No cross platform confusion: The ME-RC remote is the same remote used on all Magnum inverter/charger models in the ME, MS, MS-AE, RD, MM, and the MMS Series lines.

Multiple functional settings:

The Remote offers multiple functions in one place, including: inverter on/off, charger on/off, shore power breaker settings, AGS control, meter button, setup, and technical menus.

Adjustable settings include shore power input from 5 to 60 amps; AGS settings for voltage, temperature, quiet time, clock, and status; inverter and charger settings for search watts, battery bank size, battery type, charge rate, VAC dropout, contrast, and power saver; and tech settings for battery temperature, transformer and internal FETs, software revisions, and factory reset.

A standard 50' 4-wire, twisted pair cable allows for plenty of room to display the Remote with ease.



MODEL NUMBERS

- ME-RC50

WORKS WITH

- ME Series
- MM Series
- MM-AE Series
- MMS Series
- MS Series
- MS-AE Series
- RD Series
- RD-E Series
- MM-E Series

Features and Settings

Two-line LCD display screen	Yes
Adjustable search mode	5 to 50 watts in 5 watt increments
Low battery cutout settings	9 to 12.2 VDC (12 volt), 18 to 24.4 VDC (24 volt), and 36 to 48.8 VDC (48 volt)
Selectable battery bank sizes	200 to 2500 amp-hours in 10 amp-hour increments
Selectable battery charge profile	Flooded, AGM1, AGM2, and GEL type chemistries. Also includes custom voltage adjustment
Adjustable charge rate	0 to 100% in 10% increments
Adjustable VAC dropout	60 to 105 VAC
Adjustable LCD contrast	Yes
Factory reset	Resets to factory defaults (tech menu)

Remotes

Remotes - MM-R & MM-RC



MM-R Inverter only models



MM-RC Inverter/Charger models

The low-cost, easy-to-read MM-R and MM-RC Remotes are designed to work with the MM and MMS Series Inverters and Inverter/Chargers.

MODEL NUMBERS

- MM-R25
- MM-RC25

WORKS WITH

- MM Series
- MM-AE Series
- MMS Series
- MM-E Series

Features

LEDs	Three LEDs: Invert, AC In, and Fault Modes Six LEDs: Invert, AC In, Fault Modes, Bulk, Absorb, and Float On/Off: Turns inverter or charger on or off and defeats "search" mode
Mounting	Includes bezel for surface mount or flush mount
Included with the Remote	25' phone cable

Magnum Energy, Inc.
1111 80th Street SW, Suite 250
Everett, Washington 98203 USA

The Powerful Difference

Phone: 425-353-8833
Fax: 425-353-8390
Web: www.magnumenergy.com

Testing for specifications at 25° C
Specifications subject to change without notice.
June 2008, Rev A Part #64-0560

Authorized Magnum Dealer