



POWER BRIGHT
YOUR LEADER IN POWER SOLUTIONS

MODEL
PW3500-12

SPECIFICATION SHEET

12V DC to AC 3500 Watt Power Inverter

This heavy duty inverter plugs directly to a 12 Volt DC battery to power large appliances, air conditioners, heavy duty power tools and many other electronics in your vehicle !

This unit has the following features:

- 3500 watts continuous power
- 7000 watts peak power
- Provides 29.2 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- FOUR - 3 Prong 120 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch



CE **RoHS**
COMPLIANT

Optimum efficiency	up to 90%
No-load draw	< 0.2 amp
Output Wave Form	Modified Sinewave
Input voltage range	10-15 VDC
Over voltage shutdown	over 15 VDC
Under voltage shutdown	under 10 VDC
Low voltage alarm	Audible
Overload shutdown	Yes
Thermal shutdown	Yes
Short circuit shutdown	Yes
AC receptacle	4 three-prong receptacle
Warranty	1 year
Inverter weight	25.00 lbs
Dimensions (W x H x D)	8.9 x 6.1 x 19.9 in.

MODEL
PW3500-12
SPECIFICATION SHEET

www.PowerBright.com
© 2010 PowerBright . All rights reserved